zoom®

Adds a second phone line to existing phones

Use cordless or corded telephones to make and receive Skype calls

Displays caller's name on incoming VoIP calls

Allows switching between Skype and conventional (PSTN) calls

Three-way conferencing using PSTN and Skype lines and an ordinary phone

PSTN-to-Skype call bridging

Interactive Voice Response for voice mail access and phone system control

Provides consolidated Skype and PSTN voice mail storage on a local PC

Skype certified.

Phone Adaptor for Skype

Skype's great. Skype with your favorite phones is even better.

Model 5900

If you have Skype, you know that it runs on your PC to make phone calls easier and less expensive. If you're using a headset with Skype, you probably wish you could use normal phones. Now you can!

The Zoom Phone Adaptor for Skype lets you use your favorite phone(s) with Skype. You can plug a normal phone into the adaptor, and then make or receive calls using that phone. You can even plug in a cordless base station for 1, 2, 4, or even more cordless phones, and then make or receive calls using any of those phones!

The Zoom Phone Adaptor is easy to install and use, but it's very powerful, especially if you choose to plug the adaptor into normal phone service. Powerful bridging functions allow Skype calls to be remotely accessed from mobile phones and other conventional phone numbers. This lets you use a mobile phone ("cell phone") to make calls using Skype and save lots of money, or other phones remote from your PC.

Security on bridged calls is provided using Touchtone™ password protection.

Voice mail for both Skype and conventional calls is provided by the Model 5900, with storage and management of the voice messages on the PC. The voice mail interface and system administration prompts are provided in fourteen languages with automatic installation based on the language used for the operating system.

The Model 5900 is USB port powered to reduce power adaptor clutter. The compact size allows convenient placement in any setting.

There's no better time than now to extend the power of Skype. And there's no better way than with the Zoom Phone Adaptor for Skype.

Use Normal Phones for Skype

It's easy to extend the power and convenience of Skype:

1. Install the included software.
2. Plug the Adaptor into your computer's USB port.
3. Plug your favorite phone or cordless base station into the Adapter.
4. If you like, plug the Adaptor into a phone jack to:
   - extend Skype capabilities to mobile phones;
   - allow the phone to be used for both Skype and conventional phone calls;
   - add conferencing and call forwarding using Skype with conventional phone service
5. Enjoy the power, convenience, and low cost of Skype!

skype Certified Phone adaptor

Model 5900

Phone Adaptor for Skype

Specifications

1 FXO port, 1 FXS port

FXS Description:	- Hook state detection
	- DTMF detection
	- DTMF generation
	- Caller ID type I (on hook)
	- Caller ID type II (off hook)
	- Caller ID support for V.23 and V.202 standards
	- Call progress signal generation: Dial tone, Busy, Invalid number tones
	- Off-hook drive can drive up to two telephone sets
	- Ringer Equivalency Number (REN): 3 (can ring at least three and often more phones)
FXO Description:	- Sensing: PSTN line connected; Line in use; Ring detection; Busy detection; Silence detection with configurable duration
	- Configurable DTMF Generation: Complies with CTR 21 DTMF signaling; Configurable DTMF level and twist
	- Off hook drive can drive up to two telephone sets
Status Indicators:	- Power, PSTN Call-In-Progress, VoIP Call-In-Progress
Ports:	- USB, RJ-11 Phone port (for connection of local phones), RJ-11 Line port (for optional connection to conventional phone line)
Regulatory Approvals:	- CE, FCC Part 15B, FCC Part 68, Restriction of Hazardous Substances (RoHS) compliant, CSA International (North America safety test), Industry Canada
Dimensions:	- 10.5 x 7.9 x 2.3 cm (4.1 x 3.1 x .9 inches)
Warranty:	- Two years limited manufacturers warranty from date of purchase.

Skype certified.

System Requirements

- Pentium 600 MHz (1 GHz recommended)
- Windows 2000, XP or Vista
- Skype Softphone software
- Available USB port (USB 1.0, 1.1, or 2.0)
- 256 MB RAM recommended
- CD ROM device
- Telephone supporting DTMF (Touchtone) dialing

The Model 5900 must be connected to a USB port on a PC or to a powered USB hub, not a bus-powered USB hub

Package contents:

- Phone Adaptor for Skype
- Printed documentation
- CD ROM
- Installation Guide
- USB cable
- Telephone cord

International Headquarters
Zoom Technologies, Inc.
207 South Street
Boston, MA 02111
USA
Tel: 617 535-9383
800-631-3116
Fax: 617 423-3923
email: sales@zoom.com
www.zoom.com
Nasdaq: ZOOM

European Sales
Zoom Technologies, Inc.
Central House
2 Kings Road
Fleet, Hants
GU51 3AD UK
Tel: +44 (0) 1252 625323
Fax +44 (0) 1252 617920

©2007 Zoom Technologies, Inc., 207 South Street, Boston, MA 02111 USA
Zoom is a registered trademark of Zoom Technologies, Inc. Windows 98, Windows Me, Windows 2000, Windows NT4.0 and Windows XP are registered trademarks of Microsoft Corporation.
All other registered trademarks and trademarks used herein are the property of their respective holders.

4208 5900 skype